

ICM493-60A Single Phase Line Monitor with Built-In Surge Suppression



RV

APPLICATIONS:

APPLIANCE |

CE | ELECTRICAL | HVAC/R | MARINE | POOL & SPA |



OVERVIEW

The **ICM493-60A** is an advanced, single-phase line voltage monitor with a bank of surge arresters for added protection against lightning strikes. Includes a built-in 6oA contactor to support larger systems. Housed in a NEMA Rated 3R enclosure for outdoor installations. UL Listed. Installs easily between the service disconnect and the condensing unit. Ideal for Mini-Splits or other valuable, single-phase equipment.

FEATURES

- Protects against over and under voltage, rapid short cycling caused by transients, and high-power surges
- ✓ Fault history feature records and retains the five most recently occurred faults in non volatile memory
- ✓ Ideal for mini-splits or other condensing units
- ✓ Easy to view, backlit digital display
- ✓ Bank of five L-L surge arresters
- ✓ Built-in 6oA contactor
- ▼ NEMA Type 3R rated metal enclosure for outdoor use
- ✓ Easy installation and setup
- ✓ Limited lifetime product, up to a 3-year \$10,000 connected equipment warranty

SPECIFICATIONS

INPUT:

- Voltage: 195-264 VAC
- **Frequency:** 50/60Hz

CONTACT RATINGS:

- Voltage: 240 VAC
- **FLA:** 60A
- LRA: 360A

CONTROL OPERATING TEMPERATURE:

- **Operating temperature:** -40°F to 167°F (-40°C to 75°C)
- **Storage temperature:** -40°F to 185°F (-40°C to 80°C)
- LCD Operating temperature: -4°F to 167°F (-20°C to 75°C)

MECHANICAL:

- Mounting: Four mounting holes in back of enclosure
- Enclosure: Weather resistant, NEMA 3R rated for outdoor installation

PARAMETERS:

- Voltage: 200-240 VAC, adjustable
- Over/under voltage setting: 5%-10%, adjustable (under voltage limited to 195 VAC)
- Anti-short cycle time delay: 0.5-10 minutes
- Number of trials: 1-5, auto
- Number of movistors: 0-5

Content and specifications on sell sheets subject to change without notice.





7313 William Barry Blvd. North Syracuse, NY 13212 www.icmcontrols.com | 1-800-365-5525 | info@icmcontrols.com