

## ICM102 Delay on Make Timer



**APPLICATIONS:** 

APPLIANCE | ELECTRICAL | HVAC/R | MARINE | POOL & SPA | RV



## **REPLACES**

■ **A-1:** EAC-701-ADJ

■ **Diversified:** AC-800

■ **Gemline:** 1C310, 1C213

**Mars:** 32019, 32391, 32367

■ **Supco:** TD69

■ Wagner/DiversiTech: ADM-1

## **FEATURES**

- ▼ Universal voltage operation
- √ Higher 1.5 amp power rating
- √ Knob-adjustable time delays
- ▼ Works with anticipator-type thermostats
- √ One model replaces many in field
- √ Ideal for compressor staging
- √ Simple 2-wire hookup

## **SPECIFICATIONS**

- **Voltage:** 18-240 VAC, 1.5 amps, 15 amp inrush, 40 mA holding current
- **Frequency:** 50/60 Hz
- **Adjustable delay:** .03-10 minutes (1.8-600 seconds)
- Voltage drop: 2.5 V @ 1.5 amps

**OVERVIEW** 

When power is applied to the input, the time delay begins. After the time delay is complete, the load energizes.



