

ICM102F Delay on Make Timer with 6" Wire Leads



RV

APPLICATIONS:

APPLIANCE | ELECTRICAL | HVAC/R | MARINE | POOL & SPA |



OVERVIEW

When power is applied to the input, the time delay begins. After the time delay is complete, the load energizes.

REPLACES

- **Supco:** TD69W
- Wagner/DiversiTech: ADM-2

FEATURES

- ✓ Universal voltage operation
- ✓ Higher 1.5 amp power rating
- ✓ Knob-adjustable time delays
- ✓ Works with anticipator-type thermostats
- ✓ One model replaces many in field
- ✓ Ideal for compressor staging
- ✓ Simple 2-wire hookup
- ✓ "F" suffix denotes 6" wire leads

SPECIFICATIONS

- Voltage: 18-240 VAC, 1.5 amps, 15 amp inrush, 40 mA holding current
- Frequency: 50/60 Hz
- Adjustable delay: .03-10 minutes (1.8-600 seconds)
- Voltage drop: 2.5 V @ 1.5 amps



7313 William Barry Blvd. North Syracuse, NY 13212

Content and specifications on sell sheets subject to change without notice.

www.icmcontrols.com | 1-800-365-5525 | info@icmcontrols.com