

7313 William Barry Blvd.  
N. Syracuse NY, 13212  
United States  
1-800-365-5525  
info@icmcontrols.com



## THE NEED FOR YEAR-ROUND SURGE PROTECTION



[www.icmcontrols.com](http://www.icmcontrols.com)

## INTRODUCTION

Electrical risks to HVAC systems are not limited to a specific season—especially in tropical or warm-climate regions where weather patterns, humidity, and frequent storms create year-round surge risks. Power fluctuations can be caused by lightning strikes, grid instability, voltage sags, sudden restoration of power, or rapid cycling of high-demand equipment.

These events can produce damaging voltage spikes that affect sensitive HVAC components such as microprocessors, thermostats, variable-speed motors, and smart sensors. Without surge protection, homeowners face costly repairs, equipment failures, unexpected downtime, and decreased customer satisfaction.

This document outlines the most common sources of year-round surges, explains relevant technical specifications, such as UL 1449 Type 1 and Type 2 devices, and provides practical recommendations for selecting and installing effective protection strategies. Real-world case studies demonstrate the importance of continuous protection in environments where electrical disturbances occur frequently, regardless of the season.

## MARKET CONTECT/BACKGROUND

Power surges—brief spikes in voltage—can originate from atmospheric electrical activity, utility grid switching, or internal sources such as the on/off cycling of compressors or large appliances. Studies show that approximately 60% of surges occur inside buildings, not only from external causes.

These surges can damage HVAC components such as compressors, contactors, capacitors, motors, and electronic boards. Repair costs can range from a few hundred dollars to several thousand dollars, depending on the type of system and the severity of the event. In high-temperature or tropical climates, where electrical demand is constant and storms are frequent, the likelihood of damage increases significantly.

## REAL IMPACT AND BENEFITS

Below are examples of HVAC failures related to surges in warm or tropical regions:

- A homeowner on the Florida coast faced a \$3,000 bill when, after power was restored following a tropical storm, a surge damaged the compressor board and capacitors.
- In Texas, a high-efficiency unit failed due to a grid fluctuation that damaged the inverter board and compressor, resulting in a \$3,200 replacement. After surge protection was installed, no further failures were recorded during subsequent storms.
- Homes in Florida and Texas with comprehensive protectors saw a 40% reduction in HVAC damage during storm seasons, lowering repair costs from \$3,000 to less than \$300 per year.

A commercial installation in southern Texas reduced surge-related failures by 75% after installing industrial transient voltage surge suppressors, saving \$1,500 annually.

HVAC systems with multi-point protection show 45% fewer failures and a 30% longer service life. Protection can reduce repair costs by up to 60%, extend component life by 30%, and improve energy efficiency by 15%.

In commercial buildings, surge protection reduces downtime and automation failures, especially in regions with unstable grids or frequent electrical storms.

Surge protection offers tangible benefits by preventing damage, reducing costs, and extending the life of systems in climates where electrical disturbances occur year-round.

## UNDERSTANDING TECHNICAL SPECIFICATIONS AND THEIR IMPORTANCE

When selecting surge protection for HVAC systems—especially in tropical regions or areas with frequent storms—it is essential to consider the following:

### General Electrical Specifications

- Voltage configuration: 120VAC single-phase / 240VAC split-phase (residential), 208/240VAC or 480VAC three-phase (commercial)

- Surge current: 20,000A–100,000A
- Nominal discharge current: 5kA–20kA per phase
- Clamping voltage: ≤400V residential, ≤600V commercial
- Response time: <1 nanosecond
- Operating frequency: 50/60Hz
- Short-cycle delay: 3 minutes

### Standards & Certifications

- Type 1: Service entrance protection (whole-home protection)
- Type 2: Load-side protection (HVAC equipment)
- UL 1449 Type 1 or 2: Safety and performance
- NEMA 4X enclosure: Resistance to humidity, tropical climates, and coastal environments
- Diagnostic LEDs and warranties with coverage for connected equipment

### Recommended Devices - ICM Controls

- ICM517A
- ICM517A-Lite
- Sentry 3N1
- ICM518
- ICM530
- ICM531
- ICM493
- 3VMS-60-208
- 3VMS-60-480

### PROBLEM/SOLUTION

In warm, coastal, or tropical regions, HVAC systems are constantly exposed to grid fluctuations, atmospheric electrical activity, and voltage variations. Implementing a multi-level protection strategy ensures effective year-round defense.

### RECOMMENDED STRATEGY

- Service entrance protection: Type 1 SPD at the main panel
- Branch circuit protection: Type 2 SPDs at HVAC disconnect boxes
- Equipment-level protection: Place SPDs near sensitive components

### INSTALLATION TIPS FOR TROPICAL OR YEAR-ROUND REGIONS

### General Best Practices

- Ensure proper grounding
- Keep wires short and direct
- Verify voltage and phase compatibility
- Follow the manufacturer's instructions

### Residential

- Install SPDs in outdoor disconnect boxes
- Protect smart thermostats
- Combine whole-home protection with HVAC-specific protection

### Commercial

- Install SPDs in control and automation panels
- Use SPDs with remote monitoring
- Consider redundancy in critical environments

### BENEFITS OF IMPLEMENTING THIS STRATEGY

- Lower repair costs
- Longer system life
- Greater reliability during storms, power fluctuations, and load variations
- Less downtime and fewer emergency calls

### CASE STUDIES (TROPICAL / YEAR-ROUND VERSION)

#### Residential Case — Florida Coast

A homeowner experienced frequent failures during seasonal electrical storms. After installing a Type 2 SPD at the disconnect and a Type 1 SPD at the main panel, no damage was recorded during several electrical events, preventing more than \$2,500 in repairs.

#### Commercial Case — Office Complex in Texas

A business park experienced HVAC interruptions due to grid instability and surge events caused by lightning. With the installation of Sentry 3N1 units, the site achieved a 65% reduction in emergency calls and savings of more than \$5,000 in one year.

### CONCLUSION

Power surges represent significant risks to HVAC systems in any climate, especially in tropical or storm-prone regions where outages, electrical activity, and grid instability occur year-round. Surge protection is no longer a seasonal measure: it is an essential standard for ensuring reliability and pro-

protecting customer investments.

Adopting a multi-level protection strategy with UL 1449-certified devices helps reduce repairs, prevent interruptions, and maintain uninterrupted comfort in any climate.

## CITATION REFERENCES - ADDITIONAL SOURCES CONSULTED

1. U.S. Energy Information Administration. (2024, January 25). U.S. electricity customers averaged five and one-half hours of power interruptions in 2022. Today in Energy. <https://www.eia.gov/todayinenergy/detail.php?id=61303>
2. The Energy Mix. (2024, January 25). Storms trigger 80% of U.S. power outages over 20 years, study finds. <https://www.theenergymix.com/storms-trigger-80-of-u-s-power-outages-over-20-years-study-finds/>
3. Statista. (2023). Percentage distribution of weather-related power outages in the United States from 2000 to 2021, by cause [Graph]. Statista. <https://www.statista.com/statistics/1469809/percentage-distribution-of-weather-related-power-outages/>
4. ThorSurge. (n.d.). 4 key insights on whether power surges can damage your HVAC. <https://www.thorsurge.com/en/Blog/4-Key-Insights-on-Whether-Power-Surges-Can-Damage-Your-HVAC>
5. Rod Miller HVAC. (n.d.). How to protect your HVAC system from storms and power surges. <https://www.rodmillerrhvac.com/education/blog/how-to-protect-your-hvac-system-from-storms-and-power-surges/>
6. Indoor Temp. (n.d.). What is an electrical power surge? <https://indoortemp.com/resources/what-is-electrical-power-surge>
7. ThorSurge. (n.d.). 3 benefits of surge protection for your HVAC system. <https://www.thorsurge.com/en/Blog/3-Benefits-of-Surge-Protection-for-Your-HVAC-System>
8. ThorSurge. (2024, July 2). Top 3 myths about HVAC surge protectors. <https://www.thorsurge.com/en/Blog/Top-3-Myths-About-HVAC-Surge-Protectors>
9. Indoor Temp. (n.d.). What is an electrical power surge? <https://indoortemp.com/resources/what-is-electrical-power-surge>

## ADDITIONAL SOURCES CONSULTED

1. Pacific Northwest National Laboratory. (2025, April 25). Event-correlated outage dataset in America [Data set]. Data.gov. <https://catalog.data.gov/dataset/event-correlated-outage-dataset-in-america>
2. U.S. Energy Information Administration. (2024, January 25). U.S. electricity customers averaged five and one-half hours of power interruptions in 2022. Today in Energy. <https://www.eia.gov/todayinenergy/detail.php?id=61303>
3. Thor Systems. (n.d.). Home. <https://thorsystems.us/>
4. Transient Protection Design. (n.d.). HVAC system thermostat. <https://transientprotectiondesign.com/resources/news/hvac-system-thermostat/>
5. NEMA Surge Protection Institute. (2015). Surge protective devices for residential applications – Phase 1 final report [PDF]. <https://www.nemasurge.org/wp-content/uploads/2015/01/Surge-Protective-Devices-for-Residential-Applications-Phase-1-Final.pdf>
6. nVent. (n.d.). The applications and limitations of UL 1449 for surge protective devices (SPDs). <https://blog.nvent.com/the-applications-and-limitations-of-ul-1449-for-surge-protective-devices-spds/>
7. Transtector. (2019). UL 1449 4th edition facts [PDF]. <https://www.transtector.com/images/uploaded/UL%201449%204th%20Edition%20Facts%202019.pdf>
8. Thor Systems. (n.d.). UL 1449 4th edition specification [PDF]. <https://www.thorsystems.us/wp-content/themes/thorsystems-2023/downloads/GENERAL-UL-1449-4th-ED-D-B-SPEC%28TSI-107r31%29.pdf>

10. UL Solutions. (n.d.). Surge protection device testing and certification services. <https://www.ul.com/services/surge-protection-device-testing-and-certification-services>
11. PQ Global. (2020). UL 1449 Rev 4 [PDF]. <https://pqglobal.com/wp-content/uploads/2020/11/UL-1449-Rev-4.pdf>
12. Schneider Electric. (n.d.). Surge protective devices white paper [PDF]. [https://www.se.com/us/en/download/document/WP-50035\\_SPDs/](https://www.se.com/us/en/download/document/WP-50035_SPDs/)
13. McAllister Energy. (n.d.). HVAC surge protection. <https://www.mcallisterenergy.com/hvac-surge-protection/>
14. HVACR School. (n.d.). Surge protectors. <https://www.hvacrschool.com/surge-protectors/>
15. Heater Guides. (n.d.). Best HVAC surge protector. <https://heaterguides.com/best-hvac-surge-protector/>
16. Air Conditioner Lab. (n.d.). AC surge protector. <https://airconditionerlab.com/ac-surge-protector/>
17. DG Electrical. (n.d.). Can a surge protector help protect your HVAC system from storm damage? <https://dgelectrical.com/can-a-surge-protector-help-protect-your-hvac-system-from-storm-damage/>
18. ECI Comfort. (n.d.). How surge protectors protect your home during a storm. <https://www.ecicomfort.com/blog/how-surge-protectors-protect-your-home-during-a-storm>
19. Miller Oil Company. (n.d.). HVAC surge protection. <https://www.milleroilcompany.com/hvac-surge-protection>